

## F Series Gimbal Camera Change Frame Rate to 720p


### 1. Connect **USB to TTL** cable with gimbal and PC

Connection method:

Black wire GND ----- Gimbal GND

Green wire TX ----- TX silk printed on the gimbal controller Z-3D


White wire RX ----- RX silk printed on the gimbal controller Z-3D




### 2. Power on the gimbal, open software **VideoInConsole**

1> Finish basic settings on the software as below showing: choose correct COM number (you can check in your PC manager ). Baudrate: default is 115200. Data bit: 8, no checksum. Stop bit: 1.


2> Port status: 打开 (Open)




### 3. Choose module protocol “PelcoD 协议”



### 4. Click on “+” under “变焦”(Zoom), the image zoom in. (Communication is normal)



5. Click on “模式切换” (Change mode)



6. Click on “菜单” (Menu)




Screen will show menu as below:



7. Click “右”(Right) first, then “下” (Down) to reach “HDMI 输出” of the menu on the screen.



8. Click on “设置” (Set), and then click “右” (Right). Choose “720P”



9. Click on “设置” (Set) again. The screen will show 720P as below.



10. Click on “菜单”(Menu), quit out. Setting is done.

